



SETUP COBRANET DISCOVERY

- Go to tools>Preferences>Check Enable SNMP



- Go to tools>Options>Select the network interface connected to the CobraNet Network.
- The auto assignment can be used in cases where the new paging station device doesn't have an IP address. This will enable a type of DHCP so be careful using that on networks where some devices use automatic/DHCP because this will hand out IP addresses.




HARMAN Professional Solutions is the world's largest professional audio, video, lighting and control products and technologies company. We serve the entertainment and enterprise markets with complete system solutions.


CONFIGURE THE DEVICE

SETTING THE CURRENT IP

- Double Click on a device that you want to configure to open the interface
- Select SNMP



- Under the Group select Monitor
- Under the Variable select ipMonCurrentIP
- Selecting Get will pull the current IP address
- If you need to change the current IP address you can type it in and select put.




HARMAN Professional Solutions is the world's largest professional audio, video, lighting and control products and technologies company. We serve the entertainment and enterprise markets with complete system solutions.



SETTING A STATIC IP


- Select ipMonStaticIP under the variable
- Type in the IP address you want and select put.



SET PERSISTENCE

Last Setup persistence on the device so that the device will remember the settings after being rebooted.

- Go to Advanced



HARMAN Professional Solutions is the world's largest professional audio, video, lighting and control products and technologies company. We serve the entertainment and enterprise markets with complete system solutions.



- Make sure the persistence box is checked. Without this the device will not retain its IP address if the device is power cycled. Note: Do not change the device name on devices because this will break communication of the CM-I card with the host interface.

Advanced Configurati...

Persistence ←

Name blu-48k

Location

Contact

Conductor Priority 32

Serial Format 0x0

Serial Baud 19200

Serial PPeriod 2560

Serial RxMAC 01:60:2B:FD:00:00

SerialTxMAC 01:60:2B:FD:00:00

modeRate Control 48 kHz, 5 1/3 mS

Proc Mode N.A.

TagEnable N.A.

HMI Mode N.A.

FreeCycles 85.3%

NetMask N.A.

Refresh Apply OK Cancel

HARMAN Professional Solutions is the world's largest professional audio, video, lighting and control products and technologies company. We serve the entertainment and enterprise markets with complete system solutions.

