

Question:

How do I factory reset my LXP-5?

Answer:

Warning! This will erase all user register and patch information.

1. Unplug the LXP-5 power pack from the AC outlet.
2. Hold the LEARN button in and plug the power pack back into the AC outlet, then release the LEARN button.
3. Turn the FUNCTION knob to EDIT A.
4. Turn the SELECT knob to MIN.
5. Turn the ADJUST knob to MIN.
6. Press and release the LEARN button once. The LEARN LED should blink (RED) once.
7. Turn the Function knob to BYPASS.
8. Turn the SELECT knob to 2.
9. Turn the ADJUST knob to 2.
10. Press and release the LEARN button once. The LEARN LED should blink (RED) once.
11. Turn the FUNCTION knob to EDIT C.
12. Turn the SELECT knob to 2.
13. Turn the ADJUST knob to 2.
14. Press and release the LEARN button once again. The LEARN LED should blink (RED) once.
15. Press and release the LEARN button once again. The LEARN LED should blink (RED) steadily.
This indicates that the memory has been cleared properly.
16. Note: If the LEARN LED and the Overload LED should blink in an alternate pattern, do not be alarmed. This is only an indication that the clear memory sequence was incorrect. If this happens, repeat steps 1-15.
17. Turn the FUNCTION knob to the Pitch Preset. Press and release the LEARN button. This will exit the clear memory routine.

The LEARN LED should begin to blink (GREEN).

About HARMAN Professional Solutions

HARMAN Professional Solutions is the world's largest professional audio, video, lighting, and control products and systems company. Our brands comprise AKG Acoustics®, AMX®, BSS Audio®, Crown International®, dbx Professional®, DigiTech®, JBL Professional®, Lexicon Pro®, Martin®, Soundcraft® and Studer®. These best-in-class products are designed, manufactured and delivered to a variety of customers in markets including tour, cinema and retail as well as corporate, government, education, large venue and hospitality. For scalable, high-impact communication and entertainment systems, HARMAN Professional Solutions is your single point of contact. www.harmanpro.com