

## To format and erase the contents of the internal SD card:

1. Download firmware Zip file
2. Unzip the files to a USB key formatted to FAT32 in the root directory, there should be three files:
  1. *yourconsolename.bin*
  2. *info.xml*
  3. *Fadervl\_I\_Build13.hex*
3. Put console into Boot/Software loader mode - press and hold flashing power button.



- a. (Si Impact has a bootloader button located on the back of the console that will need to be engaged when flipping the power switch).



4. Insert the USB stick and then press the MENU key.
5. If the fader firmware requires updating this will be prompted on the touch screen; follow on-screen instructions for this process.
6. Select the INFO.XML file using the scroll/adjust encoder, the LOAD button at the bottom right of the touch screen window will appear when a valid selection is made.



7. Press the LOAD button. Software will begin loading.
8. Wait until both progress bars have reached 100%, and the 'tick' symbol has appeared to the right of each progress bar, before removing the USB stick.
9. Reboot console normally.

#### About HARMAN Professional Solutions

HARMAN Professional Solutions is the world's largest professional audio, video, lighting, and control products and systems company. Our brands comprise AKG Acoustics®, AMX®, BSS Audio®, Crown International®, dbx Professional®, DigiTech®, JBL Professional®, Lexicon Pro®, Martin®, Soundcraft® and Studer®. These best-in-class products are designed, manufactured and delivered to a variety of customers in markets including tour, cinema and retail as well as corporate, government, education, large venue and hospitality. For scalable, high-impact communication and entertainment systems, HARMAN Professional Solutions is your single point of contact. [www.harmanpro.com](http://www.harmanpro.com)